
Oxygen CiTiceL® Specification



70X-V CiTiceL®



Performance Characteristics

Physical Characteristics

Nominal Range	0-25% Oxygen Storage Life		Six months in CTL container	
Max Overload	30% Oxygen	Recommended Storage		0-20°C
Expected Operating Life	Two years in air		Temperature	
Output Signal	0.195 - 0.25mA in air		Warranty Period	24 months from date of despatch (This amounts to a variation of condition 6 of our standard terms and conditions which otherwise apply)
$T_{_{95}}$ Response Time	≤15 seconds			
Offset (3mins N ₂)	<0.5% O ₂			
Temperature Range	-20°C to +50°C	N.B. All performance data		a is based on conditions at 20°C,
Temperature Coefficient	0.2% signal/°C		50%RH, and 1013m	nBar
Absolute Pressure Range	Atmospheric ± 10%			
Differential Pressure	0 to 40mBar max			
Range				
Pressure Coefficient	<0.02% signal/mBar			
Operating Humidity intermittent continuous	0 to 99% RH non-condensing 15 to 99% RH non-condensing			
Long Term Output Drift	<5% signal loss/year			
Recommended Load Resistor	100Ω			
Doc. Ref.: 7oxy Issue 1.2	Page 1 of 2			19th October 2004

Doc. Ref.: 7oxv Issue 1.2

Page 1 of 2

19th October 2004

City Technology Ltd, City Technology Centre, Walton Rd, Portsmouth PO6 1SZ, UK Tel:+44 23 9232 5511, Fax:+44 23 9238 6611, sensors@citytech.co.uk, www.citytech.com

Oxygen CiTiceL® Specification




Temperature Behaviour

1) Gradual changes

The output of a 7OX-V CiTiceL varies slightly with gradual temperature changes. The behaviour of a batch of 7OX-V sensors is shown opposite. Output was measured at a range of temperatures and expressed as a percentage of the signal at 20°C. The graph shows the mean signal and three times standard deviation.

2) Sharp fluctuations

A transient response will occur with sharp fluctuations in temperature. For rapid increases in temperature there is a sharp drop in sensor output, and a sharp increase in output for rapid decreases. These responses are transient and should die away in about 20 seconds.



Linearity


The output signal of an Oxygen CiTiceL follows the relationship:

 $S = K \log_{2} 1/(1-C)$

where:

S = Output signal; C=Fractional oxygen concentration; K = a constant for the sensor.

For most applications the deviation from a linear response will be insignificant, and no compensation needed. For example, the graph below shows the output of a sensor calibrated in air $(20.9\% O_2)$. In this case the maximum error in the 0-25% range is >0.5% at around $10\% O_2$.



Every effort has been made to ensure the accuracy of this document at the time of printing. In accordance with the company's policy of continued product improvement City Technology Limited reserves the right to make product changes without notice. No liability is accepted for any consequential losses, injury or damage resulting from the use of this document or from any omissions or errors herein. The data is given for guidance only. It does not constitute a specification or an offer for sale. The products are always subject to a programme of improvement and testing which may result in some changes in the characteristics quoted. As the products may be used by the client in circumstances beyond the knowledge and control of City Technology Limited, we cannot give any warranty as to the relevance of these particulars to an application. It is the clients' responsibility to carry out the necessary tests to determine the usefulness of the products and to ensure their safety of operation in a particular application.

Performance characteristics on this data sheet outline the performance of newly supplied sensors. Output signal can drift below the lower limit over time.

Doc. Ref.: 7oxv Issue 1.2

Page 2 of 2

19th October 2004

City Technology Ltd, City Technology Centre, Walton Rd, Portsmouth PO6 1SZ, UK Tel:+44 23 9232 5511, Fax:+44 23 9238 6611, sensors@citytech.co.uk, www.citytech.com